



AC-8

NON-CONTACT AC VOLTAGE DETECTOR

- | Non-Contact Detection of AC Voltage 100~1000VAC (50/60Hz)
- | Rugged, double molded case
- | Used to find a break in a wire or detect the presence of voltage at outlets, lighting fixtures, circuit breakers, wires and cables
- | Bright LED and buzzer alarm if Voltage is present
- | Built-in bright flashlight with ON/OFF button
- | Convenient size with pocket clip
- | An essential tool for every electrician and tradesperson

AC-8

Non-Contact AC Voltage Detector



Application

The Volt finder voltage detector is intended to check the presence of AC voltage. The presence of live voltage is signaled with a LED and Buzzer. Has Built-in bright flashlight with ON/OFF button and audible beeper indicator. Built-in Flashlight helps accessing dark areas.

This instrument confirms to CAT-III 1000V, CE.

General Specifications

Detection voltage range	100V AC to 1000 VAC, 24V AC to 1000V AC
Power	3V (AAA*2) alkaline battery
Operating temperature	-10°C to 50°C (14°F to 122°F)
Storage temperature	-10°C to 50°C (14°F to 122°F)
Humidity	95% {0°C to 30°C (32°F to 86°F)}
Altitude	3000m
Contaminated distinction	II
Weight	48.5g

Accessories

Battery, Instruction Manual.



AAYUSH ELECTRICALS & INSTRUMENTATION

ISO 9001-2015 CERTIFIED COMPANY

Office Address : # 1, 1st Main, 2nd Cross, Maruthinagar, Bengaluru, Karnataka - 560 026. India

Factory Address : #18 ,4th A Main Road, Bahubali Nagar, Jahalli Village, Bengaluru - 560013

Email : sales@aayushei.com / marketing@aayushei.com / accounts@aayushei.com

Web : www.aayushei.com , Mob : +91 88922 55555 / 96639 82272/ 88922 77777



QMS/019303/1120