


The high voltage insulation resistance tester is a handheld instrument designed primarily to make AC/DC voltage, resistance, Continuity test I insulation resistance measurement.



DT-6605

DIGITAL HIGH VOLTAGE INSULATION TESTER

Safety Information



DT-6605 Digital High Voltage Insulation Tester

Features

The Tester is a micro computer controlled, High Voltage Insulation Resistance Tester with 4-range for measuring insulation resistance and AC/DC Volage, Resistance/Continuity test

- I Designed to following safety standards:
 - IEC 61010-1 (CATIV 600V Pollution degree 2)
 - IEC 61010-031 (Requirements for hand-held probes)
- I Insulation test range : $0.1M\Omega$ to $60G\Omega$
- I Insulation test voltages : 500V/1000V/2500V/5000V
- I AC/DC Voltage : 0.5V to 600V
- I 200mA Continuity
- I Resistance : 0.1Ω to $6k\Omega$
- With auto-discharge function & voltage output warning function
- I When insulation resistance like a capacitive load is measured, electric charges stored in capacitive circuits are automatically discharged after measuring. Discharge can be checked with live voltage graph
- I Backlight levels selector function to facilitate working at dimly illuminated location or at night time work
- I Live circuit warning symbols plus audible warning
- Live circuit detection prevents insulation test if voltage >30V is detected for added user protection
- I With Auto-power off function & battery check
- I With Time measurement function
- I Automatically performs a measurement at the set time
- I With Polarization Index measurement (PI)
- I The Polarization Index can be measured by the automatic measurement function of the ratio of resistance in 1min. and 10 min. two point time and automatic (Pass/Fail)
- I With Dielectric Absorption Ratio measurement (DAR)
- I The Dielectric Absorption Ratio measured by the automatic measurement function of the ratio of resistance in 30sec. and 1 min. two point time and automatic (Pass/Fail)
- I Auto ranging with larger 6000 counts LCD display with bargraph
- I MAX/MIN, PEAK. Relative Value & Data Hold Functions for DC/AC voltage measurements
- Power source 1.5V x 8 (LR14/R14) Batteries

Technical Specifications

Open Circuit Test Voltage ≥ 4.5V

	surement				
Rated Voltage	500V	1000V	2500V	5000V	
Measuring Range (Auto-Ranging)	0.005 to 6.000 M Ω	0.005 to 6.000 M Ω	o.os to $60.00 M\Omega$	0.05 to 60.00MΩ	
	6.01 to 60.00MΩ	6.01 to 60.00MΩ	60.1 to 600.0MΩ	60.1to 600.0MΩ	
	60.1 to 600.0MΩ	60.1to 600.0MΩ	0.61 to 6.00GΩ	0.61 to 6.00GΩ	
	0.61 to 6.00GΩ	0.61 to 6.00GΩ	6.1to 60.0GQ	6.1 to 60.0GΩ	
Open Circuit Voltage	DC 500V +20%,-0%	DC 1000V +20%,-0%	DC 2500V +20%,-0%	DC 5000V +20%,-0%	
Rated Current	1to 1.2mA (at 0.5Mn load)	1 to 1.2mA (at 1Mnload)	1to 1.2mA (at 2.SMn load)	1 to 1.2mA (at 5Mn load, Recommended use of the Power Adaptor)	
Short Circuit Current	Approx.1 mA				
Accuracy	$\pm 2.5\%$ reading ± 15 digits (at 0.005 to 600.0M Ω)				
	$\pm 3\%$ reading ± 15 digits (at 0.61 to 6.00G Ω)				
	$\pm 4\%$ reading ± 15 digits (at 6.1 to 60.0G Ω)				
Voltage Monitor Range	5 to 6000VDC (Resolution 1V); Accuracy ±1.5%reading ±5digits				
DC/AC Voltage Measurem	ent				
	Range	Resolution	Accuracy		
DC Voltage	0.5 to 600.0V	0.1V	±1.0% reading ±5digits		
AC Voltage (40 to 400Hz)	0.5 to 600.0V	0.1V	±1.0% reading ±5digits (40 to 60Hz) ±2.5% reading ±10digits (61 to 400Hz)		
	nent Continuity Check				
Low Resistance Measurem	T	Resolution	Accuracy		
Low Resistance Measuren	Range	nesonation.	±1.5% reading ±10digits		
	Range 0.1to 600.0n	ο.rΩ	±1.5% reading ±10dig	its	
Low Resistance Measuren Resistance (Auto-Range)	_		±1.5% reading ±10dig ±1.5% reading ±15dig		
	0.1to 600.0n	ο.rΩ			

DT-6605 Digital High Voltage Insulation Tester

General Specifications

Applicable standards	IEC 1010 CAT IV 600V overvoltage and double insulation standard
Display	6000 counts LCD display with bargraph
Sampling rate	2.5 readings per second
Over range indicator	"OL" displayed
Fuse	500mA 600V (6X32mm) ceramic 3AG Fast blow
Zero adjust Automatic Auto power off	Power off function operates automatically after a switch remains for 20min (current consumption approx. $50\mu A$).
Low Battery Indicator	Low battery symbol displayed when battery voltage is low
Environmental Installation	Category II, Pollution Degree 2, Altitude up to 2000 meters, Indoor use only
Power Source	8 x 1.5V(R14) batteries
Operating Conditions	o to 40°C(32 to 104°F); <80%RH
Storage Conditions	-10 to 60°C(14 to 140°F); <80%RH
Dimensions	198(L) x 148(W) x 86(D)mm
Weight	1438g

Accessories

Item	Description	Qty		
1	User Manual	1 piece		
2	One plug test lead to one alligator clip (Black colour)	1 piece		
3	One plug test lead to one alligator clip (Green colour)	1 piece		
4	One plug test lead to one alligator clip (Red colour)	1 piece		
5	Two plugs test lead to one alligator clip (Red colour)	1 piece		
6	1.5V Battery_(LR14)	8 pieces		
7	Carrying Case	1 piece		
8	Power adaptor (input voltage 110V to 230V. 50/60Hz, 75mA. output DC 13.5V.1.0A) (Optional available at extra cost)	1 piece		





AAYUSH ELECTRICALS & INSTRUMENTATION ISO 9001-2015 CERTIFIED COMPANY

Office Address: #1, 1st Main, 2nd Cross, Maruthinagar, Bengaluru, Karnataka - 560 026. India Factory Address: #18,4th A Main Road, Bahubali Nagar, Jahalli Village, Bengaluru - 560013 Email: sales@aayushei.com / marketing@aayushei.com / accounts@aayushei.com Web: www.aayushei.com , Mob: +91 88922 55555 / 96639 82272/ 88922 77777



