



## AC-10

### NON-CONTACT AC VOLTAGE DETECTOR WITH FLASHLIGHT

- | Green Light when it is turned ON
- | Red Light when voltage is detected
- | Audible and Light indication for Low Battery, Power On and Voltage Detection

# AC-10

## Non-Contact AC Voltage Detector With Flashlight



### General Specifications

Voltage range	50 V AC to 1000 V AC (50/60Hz)	
Type	Non-Contact Voltage Detector	
Voltage Detection Indicators	Visual High intensity Red LED	
	Audible : Discontinuous Beeping Sound	
Operating conditions	Temperature	0°C to 40°C (32°F to 104°F)
	Relative Humidity	<80%
	Altitude	Up to 6,562 feet (2,000 meters) maximum
	Environment	Indoor Use
Power On Indication & Illuminator	Visual	High Intensity Green LED
Power Off & Auto Power Off	Visual	Power-On LED turns off
	Audible	Continuous Beeping Sound
Low Battery Indicators	Visual	Green LED Blinks
	Audible	Series of Beeping Sounds
Batteries	Two "AAA" 1.5V batteries	
Pollution Degree	2	

Safety Complies with EN 61010-1 2nd Edition, EN 61326 EMC to 1000 V CAT IV

### Accessories

Battery, Instruction Manual.



## AAYUSH ELECTRICALS & INSTRUMENTATION

ISO 9001-2015 CERTIFIED COMPANY

Office Address : # 1, 1st Main, 2nd Cross, Maruthinagar, Bengaluru, Karnataka - 560 026. India

Factory Address : #18 ,4th A Main Road, Bahubali Nagar, Jahalli Village, Bengaluru - 560013

Email : [sales@ayushel.com](mailto:sales@ayushel.com) / [marketing@ayushel.com](mailto:marketing@ayushel.com) / [accounts@ayushel.com](mailto:accounts@ayushel.com)

Web : [www.ayushel.com](http://www.ayushel.com) , Mob : +91 88922 55555 / 96639 82272/ 88922 77777



QMS/019303/1120