

This is a pocket type Digital Thermometer that can measure from -50 to 200°C. This instrument has Auto Power Off function, Alarm set for high and low values and has MAX/MIN record function.



DT-1370 Digital Thermometer

Electrical Specifications

Temperature Range	-50 °C to +200°C (-58°F to +392°F)
Accuracy	± 2 °C± 4°F)
Resolution	0.1 °
Measurement Rate	1 time per second
Auto Power Off	10 minutes
HI/Low Temperature Alarm	
Low Battery Indication	
Alarm Temperature Range	-40°C to +200°C (-40°F to +392°F)

Accessories

Temperature Probe, Battery, Instruction Manual.







